

Supreme-H

Analog Addressable
Fire Control Panels
(2 or 4 Loops)
(Hochiki Protocol)



AS1420-xx (2 Loops)

AS1440-xx (4 Loops)

where xx = 10 for Red & 40 for Gray

Standard Features

- UL 864 9th Edition listed
- Multi-Loop 2 Analog Addressable Loops Field upgradable to 4
- We can use 254 address points
- Powerful, network wide cause and effects (500 total). Fully user programmable by point or zone.
- Up to 800 points per panel when using devices and sub-points
- Up to 10,000 ft. wiring length on SLC loop
- 64 Panels on a network
- Programmable through a PC connection to the panel, or through keypad
- Programmable on-board relays – 5
- Supervised Powered Outputs – 3
- Programmable Notification Appliance Circuits: 4
- Power per NAC: 1.6 Amps Max
- Programmable outputs on SLC loop
- Programmable Function button on front display
- Fire Drill button on front display
- Day and night sensitivity settings (user programmable)
- Power Supply: 5.25 Amp, regulated & integrated
- LCD Display: 8x40
- Zonal Mode: Annunciation by zone w/o individual relationships
- Panel Ring Modes: Common, Zonal, Stage 2
- NAC Outputs programmable as Continuous, March, Temporal
- Program Cause and Effects AND, OR, or Any Two (Cross Zone)
- Battery size: Up to 17 Ah in standard enclosure; up to 52 Ah with external cabinet
- Access levels: 3
- Access key switch: Yes
- Recognized for use in High Rise
- One man walk test – Fire Test Mode
- Available with semi flush trim ring
- Available in Red or Gray

Product Overview

- The AS1420 and AS1440 analog addressable FACP with networked releasing, supports 2 or 4 SLC loops for a total of 500 primary points and up to 800 points using subpoints. SLC loop communications uses standard twisted pair cabling, shielded cable is not necessary.
- The panel may be configured with various communication cards; Communications options support remote programming, central station monitoring, Virtual Panel and networking.
- The Panel can be configured as a stand-alone panel with just a few devices for a small building; it can also operate as the building system and can be part of a network with a total of 64 nodes serving a multiple building campus or a very large facility.
- Auto Learn capability provides a convenient method to troubleshoot new installations before final programming is loaded.

